

2525/01

Friday 12 June 2009
Morning

Duration: 1 hour



- This document consists of 4 pages. Any blank pages are indicated.

General

Area of rectangle $= l \times w$

Area of triangle $= \frac{b \times h}{2}$

Area of circle $= \frac{\pi d^2}{4}$

Circumference of circle $= \pi d$

Volume of rectangular prism $= l \times w \times h$

Volume of cylinder $= \text{area of base circle} \times h$

Volume of cone $= \frac{\text{area of base circle} \times h}{3}$

Electrical and Electronic Systems

$$V = I \times R$$

$$W = V \times I$$

Resistors in series $R_{total} = R_1 + R_2 + R_3 \text{ etc.}$

Resistors in parallel $\frac{1}{R_{total}} = \frac{1}{R_1} + \frac{1}{R_2} + \frac{1}{R_3} \text{ etc.}$

OR

$$R_{total} = \frac{R_1 \times R_2}{R_1 + R_2}$$

Potential Divider $V_{out} = V_{in} \times \frac{R_2}{R_1 + R_2}$

Capacitor time constant $T = C \times R$

Capacitors in series $\frac{1}{C_{total}} = \frac{1}{C_1} + \frac{1}{C_2} + \frac{1}{C_3} \text{ etc.}$

Capacitors in parallel $C_{total} = C_1 + C_2 + C_3 \text{ etc.}$

Mark space ratio $= \frac{T_{on}}{T_{off}}$

Astable frequency (f) $= \frac{1}{1.4 \times C_1 \times R_1}$

555 astable frequency (f) $= \frac{1.44}{(R_a + 2R_b)C}$

output high time $= 0.693(R_a + R_b)C$

output low time $= 0.693(R_b)C$

555 monostable time constant

on time $= 1.1R_a C$

Voltage gain $= \frac{V_{out}}{V_{in}}$

Non inverting amplifier $V_{out} = V_{in} \times \frac{(R_f + R_{in})}{R_{in}}$

Inverting amplifier $V_{out} = -V_{in} \times \frac{R_f}{R_{in}}$

Summing amplifier $V_{out} = -R_f \times (\frac{V_1}{R_1} + \frac{V_2}{R_2} + \frac{V_3}{R_3})$ etc.

Differential amplifier $V_{out} = \frac{-R_f}{R_a} \times (V_2 - V_1)$

MOSFET $g_m = \frac{\Delta I_d}{\Delta V_{gs}}$

Battery life battery capacity = current x time

Mechanical Systems

Moment = force x perpendicular distance

Stress $= \frac{\text{force}}{\text{cross sectional area}}$

Strain $= \frac{\text{change in length}}{\text{original length}}$

Young modulus of elasticity $= \frac{\text{stress}}{\text{strain}}$

Work done = force x distance moved

Power = force x velocity

Work done = torque x angle turned
 Power = torque x angular velocity

Pneumatic Systems

Force = pressure x area
 Compression ratio = $\frac{\text{gauge pressure} + \text{atmospheric pressure}}{\text{atmospheric pressure}}$
 Volume of air used = area x stroke x compression ratio
 Lifting load = vacuum level x area



Copyright Information

OCR is committed to seeking permission to reproduce all third-party content that it uses in its assessment materials. OCR has attempted to identify and contact all copyright holders whose work is used in this paper. To avoid the issue of disclosure of answer-related information to candidates, all copyright acknowledgements are reproduced in the OCR Copyright Acknowledgements Booklet. This is produced for each series of examinations, is given to all schools that receive assessment material and is freely available to download from our public website (www.ocr.org.uk) after the live examination series.

If OCR has unwittingly failed to correctly acknowledge or clear any third-party content in this assessment material, OCR will be happy to correct its mistake at the earliest possible opportunity.

For queries or further information please contact the Copyright Team, First Floor, 9 Hills Road, Cambridge CB2 1PB.

OCR is part of the Cambridge Assessment Group; Cambridge Assessment is the brand name of University of Cambridge Local Examinations Syndicate (UCLES), which is itself a department of the University of Cambridge.